

Body-Pack RF Receiver UR-96BP



Body-Pack radio frequency Receiver with 96 selectable channels

Specifications

Operating Frequency Band	640–664 MHz
Selectable Channels	96 Pre-Programmed
Maximum Deviation	80 kHz, with Level Limiting
Dynamic Range	> 80 dB
THD	< 1%
Pre/De-emphasis	< 50 μ s
Audio Outputs	Aux Out, 3.5 mm 3.5 mm Ear Phone Jack
AF Control	Hi/Mid/Low Aux Out Switch
Battery	1.2 v NiMH rechargeable x2 or 1.5 v Alkaline x2
Operating Life (full charge)	14 hrs. (NiMH) or 17 hrs. (Alkaline)
Housing	Aluminum
Dimensions	1" D x 2½" W x 3¾" H
Weight (with batteries)	10.5 oz.

Features

- 96 UHF Channel Selectable
 - Push-button Channel Select
 - LCD Readout
 - Selected Channel #
 - Frequency
 - Battery Condition
 - Aux Output 3.5mm
 - Low Battery Power Consumption
 - Durable Metal Case
 - Hi/Mid/Low Aux Out Sensitivity Switch
 - Ear Phone Volume Control
 - Metal Belt Clip
 - Drop-In Charger Compatible
 - Requires two "AA" batteries
- Optional**
- Rechargeable Batteries, "NiMH" Duracell
 - Drop-In Charger
 - BRC-70 for Handheld or Bodypack
 - BRC-75 Dual Bodypack