

# Drop-In Charger BRC-50



Drop-in Charger for Handheld (IRH-30N & IRH-35), Crescent (IRT-30) & Body-Pack (IRB-30) transmitter

## Specifications

Charging Slots	Two Handheld, Slots A & C One Crescent, Slot B One Body-Pack, Slot D
Charging Mode	Switching
Charging Current	1700ma ±10%
Discharge Rate	350ma
Red LED Indicator	Batteries being Charged
Green LED Indicator	Batteries Fully Charged
Yellow LED Indicator	Batteries being Discharged
Recycle Button (Grey)	Press for Full Discharge and Auto Recharge
Auto Switching	Switch from Discharge to Charge Mode
Charging Time	1.5Hr./Slot
Power Supply	12VDC/1.5A (Fuse protected)
Dimensions	6½" L x 3 3/8" W x 1 1/8" H
Weight	12.2 oz.

## Features

- Convenient drop-in insertion
- Optimum charging rate for NiMH battery
- Auto charge/maintenance
- Charging mode indicator—Red LED
- Full charge indicator—Green LED
- Recycle function: periodic battery rejuvenation to maintain and extend battery service life
- Non-rechargeable battery prevention
- Clip to lock in Crescent Transmitter